

WIZARD Outboard Motors Specification Chart

Model Name	Model #	Year	Serial #	HP	Bore	Stroke	Displace- ment	Gear set	Blades	Prop Size	Prop #	Spark Plug
6 Horsepower	WD-4	1946	na	6	2	1 3/4	11cube	14/19	2	7 1/2x7	48-24418	J8J
Deluxe	WD-3	1947	na	3.2	2	1 3/4	5.5	12//22	2	7 1/2x7	48-24418	J7J
Deluxe	WD-3S	1947	na	3.2	2	1 3/4	5.5	12//22	2	7 1/2x7	48-24418	J7J
6 Horsepower	WD-4	1947	na	6	2	1 3/4	11	12//22	2	7 1/2x7	48-24418	J8J
6 Horsepower	WD-4S	1947	na	6	2	1 3/4	11	14/19	2	7 1/2x7	48-24418	J8J
Deluxe	WD-3S	1948	na	3.2	2	1 3/4	5.5	14/19	2	7 1/2x7	48-24418	J7J
6 Horsepower	WD-4S	1948	na	6	2	1 3/4	11	12//22	2	7 1/2x7	48-24418	J8J
Super Twin	WF-4	1949	304,551 319,553	6	2	1 3/4	11	14/19	2	7 5/8x7	48-24448	J7J
Super Twin	WF-4	1950	379-652 387-685	6	2	1 3/4	11	16/21	2	7 5/8x7	48-24448	J7J
Super Ten	WF-7	1950	408-293 413-300	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x11	48-24484	J8J
Super Twin	WG-4	1951	450-696 453-195	6	2	1 3/4	11	16/21	2	7 5/8x7	48-24448	J7J
Super Ten	WG-7	1951	458-196 465-695	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-23660	J8J
Super Twin	WG-4	1952	507-512 517-511	6	2	1 3/4	11	16/21	2	7 5/8x7	48-24448	J7J
Super Ten	WG-7	1952	495-762 499-261	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-23660	J8J
Super 10	WG-7	1952	534-913 535-012	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-23660	J8J
Powermatic 10	WH-7	1952	521-103 525-102	10	2 11/32	2 1/8	18.34	16/21	2	9.5x10.5	4820325A5	J8J
Super Twin	WG-4	1953	540-763 557-588	6	2	1.75	11	16/21	2	7 5/8x7	48-24448	J7J
Super Twin	WG-4	1953	572-128 574-127	6	2	1.75	11	16/21	2	7 5/8x7	48-24448	J7J
Super Ten	WG-7	1953	564-118 568-117	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-23660	J8J
Super Ten	WG-7A	1953	591-628 593-627	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-24499	J8J
Powermatic 10	WH-7	1953	568-118 572-117	10	2 11/32	2 1/8	18.34	13/24	2	9.5x10.5	4820325A3	J8J
Super Twin	WG-4	1954	719-088 733-087	6	2	1 3/4	11	16/21	2	7 5/8x7	48-24448	J7J
Super Ten	WJ-7	1954	733-088 743-067	10	2 11/32	2 1/8	18.34	16/21	3	7 1/2x10	48-24616	J8J
Powermatic 12	WK-7	1954	740-088 743-087	12	2 11/32	2 1/8	18.34	13/24	2	9.5x10.5	4820325A3	J7J
Super Ten	WM-7	1955	826-920 830-919	10	2 7/16	2 1/8	19.8	16/21	3	7.5x9	48-22798	J7J
Super Ten	WM-7	1955	915-751 917-750	10	2 7/16	2 1/8	19.8	16/21	3	7.5x9	48-22798	J7J
Powermatic 12	WN-7	1955	845-973 851-972	12	2 7/16	2 1/8	19.8	13/24	2	9.5x10.5	4820325A3	J6J
Super 5	WM-6	1956	835-971 845-970	5	1 3/4	2 1/8	7.2	14/23	2	6.75x6.25	48-24459	J7J
Super Ten	WM-7A	1956	917-751 922-750	10	2 7/16	2 1/8	19.8	16/21	3	7.5x9	48-22798	J7J
Powermatic 12	WM-7A	1956	923-251 931-750	12	2 7/16	2 1/8	19.8	13/24	2	9.75x11	4823647A1	J6J
Super Power	WA-25	1956	907-751 912-750	25	2 7/64	2 1/8	29.78	13/24	2	9.75x11.7	4825419A1	J6J
Super Power	WA-25E	1957	912-751 913-755	25	2 7/64	2 1/8	29.78	13/24	2	9.75x11.7	4825419A1	J6J
Super 5	WH-6A	1957	931-751 936-750	5	1 3/4	1 1/2	7.2	14/23	2	6.75x6.25	48-22820	J7J
Super 5	WH-6A	1957	936-751 941 750	5	1 3/4	1 1/2	7.2	13/17	2	6.75x6.25	48-22820	J7J
Super Power	WA-25	1957	1,012,962-1,018,661	25	2 7/64	2 1/8	29.78	13/24	2	9.75x11.7	4825419A1	J6J
Super Power	WA-25E	1957	1,018,662-1,019,961	25	2 7/64	2 1/8	29.78	13/24	2	9.75x11.7	4825419A1	J6J