# 

# OUTBOARD MOTOR



# 15 H. P.

MODEL M-6N-GS

FORWARD-NEUTRAL-REVERSE

OPERATING INSTRUCTIONS and REPLACEMENT PARTS



## MODEL M-6N-GS

#### SPECIFICATIONS

Model	M-6N-GS Feather-lite "15"
Gearshift	Forward - Neutral - Reverse
Horsepower	15 H.P. O.B.C. certified
Two Cylinder	Bore 21/4" Stroke 2.1/32"
Piston Displacement	19.94 cu. in. Dual rotary valve, 2 port
Valves	Dual rotary valve, 2 port
	Carter concentric bowl type
	Phelon Waterproof Hot Spark Magneto
Starter	Automatic Rewind
Steering	Automatic co-skipper
Water Pump	Positive Rotary
Controls	Positive Rotary Twist Grip Controls
Spark Plugs	Champion J8J - 14 mm.
Connecting Rods Fo	rged steel with Torrington needle bearings
Lubrication Pressure lubricate	d main, crankshaft and wrist pin bearings
Propeller	8x11, 3 blade
Drive Gears	Zerol cut for quiet operation 14 to 24
Gear reduction	14 to 24
Gas Tank, Separate Cruising	6 gal. capacity
Die-cast aluminum parts, Alrol	treated to prevent salt water corrosion
Speed Range	0 to 30 miles per hour
Weight	54 lbs.

#### PLEASE NOTE!

We reserve the right to change motor specifications contained herein without notice. Any parts contained in your motor that are different from those listed in this parts book were changed either to improve your Motor or were necessary due to material substitutions.

# Outboard Motor Brands, Inc.

1325 N. E. Quincy

Minneapolis 13, Minnesota

## INSTRUCTION MANUAL

#### Read Before Operating Your Outboard Motor

For satisfying and trouble free service, let's get acquainted with your new Outboard Motor.

#### OPERATING PROCEDURE

Your new Outboard Motor is a two cycle engine and the lubrication of the Pistons, Cylinders, Connecting Rods and Crankshaft Bearings is supplied by oil mixed with gasoline. The proportions of this mixture and the grades of gasoline and oil used are very important.

We recommend the use of any high grade Outboard Motor Oil which will mix readily with gasoline. Mix oil with any regular grade of gasoline (72 Octane rating or better), using ½ pint of oil to one gallon of gasoline for normal operation after break-in period.

#### TO START COLD MOTOR

For the first 5 hours of operation this motor should not be run faster than ¾ throttle. We recommend the use of ¾ pint of outboard motor oil to each gallon of gasoline during the break-in period.

- Open Gas Cap Vent in the separate Cruising Tank.
- Connect Gas Line Coupler by depressing knurled section, placing coupler in position on Gas Line Nipple on motor, and releasing.

- Open high speed adjustment valve approximately 1½ turns when motor is cold.
- Prime motor by repeated squeezing of primer section of Fuel Line until this section becomes firm. (Priming will vary with completely dry to semi-full system.)
- 5. Turn twist grip control to START position.
- Shift Lever should be in the Forward or Neutral position. However, a cold motor may start better with controls set at medium Forward Throttle.
- 7. Pull out choke knob to choke. Pull Starter Handle until starter engages, then pull forcibly using a quick motion. Don't pull more than three or four times in choked position. Push knob in to release choke after motor starts.
  - Should motor slow down after starting, choke quickly once or twice and squeeze primer section to see that fuel line is full.
  - Re-starting may usually be done by just resetting controls and pulling Automatic Rewind Starter a time or two.
- Usually a motor that is still warm from running requires no more than one or two pulls of the starter cord. Try this before using choke.

#### RUNNING

- When motor is warm, set High Speed Adjustment Knob at best running position.
- Throttle and spark are synchronized and regulated by twist grip control. Its range is indicated on the upper engine cover.
- 3. WARNING-Shift in indicated range only.

#### **AUTOMATIC REWIND STARTER**

When starting motor pull starter cord knob straight out approximately 24 inches, using a quick motion. It is not advisable or necessary to pull the cable a greater distance.

Should Automatic Rewind Starter fail to operate, remove the starter housing by removing the three screws that hold housing to upper engine cover. This will give access to the emergency starter plate.

#### PROPELLER SHEAR PIN

This soft "safety pin" shears when you strike an obstruction at full speed, thus protecting the gears, shafts and other mechanism of your motor from damage. When this happens shut your motor off immediately. To replace shear pin, set shift lever in reverse, remove the cotter pin in the propeller nut and remove nut. Slip off the propeller and replace the broken pin. Replace propeller, nut and cotter pin. The nut should be drawn up until the propeller fits snug against the shear pin.

#### GEAR SHIFT INSTRUCTIONS

- The Gear Shift Lever should be kept in neutral position when the motor is not in use.
- When starting motor in neutral, twist grip control may be set so that indicator is in start position. However, before shifting, set twist grip control so that indicator is in shift range as noted on upper engine cover.
- When shifting into reverse, slow motor down to Shift Range position to allow locking of the Reverse Lock. (If the motor should tilt up while shifting, slow motor down.)
- In shifting from reverse into forward, turn twist grip control so that indicator is in shift range position, shift to forward and then turn twist grip control to desired speed.

#### SPARK PLUG ADJUSTMENTS:

The spark plugs should be kept clean and the point gap set at .030 inch. If the points are too badly corroded or burned away from long use, the plug should be replaced.

#### CARBURETOR ADJUSTMENTS

- Close idle adjustment screw until it is snug (do not force needle against seat). Then open idle screw approximately <sup>3</sup>/<sub>4</sub> turn.
- Turn high speed adjustment knob until Closed. Then open approximately 1½ turns.
- 3. After starting motor, turn twist grip control until indicator is in a position slightly beyond "Start." Turn the High Speed Adjustment Knob clockwise until the motor begins to slow down from lack of gas. Then re-open high speed adjustment until motor picks up speed and runs smoothly.
- 4. Move twist grip control to position marked "Slow on upper engine cover. The motor should now idle slowly. However, atmospheric changes and fuel mixtures may require opening or closing the idle adjustment screw slightly.

#### **MAGNETO ADJUSTMENTS:**

Ordinarily these magnetos will operate over extremely long periods of time without the need for adjustment or repair. However if engine operating difficulties are experienced which appear to be caused by the ignition system, the magneto output can be checked to determine whether this unit is functioning properly.

Disengage the high - tension cable from each spark plug. Remove spark plugs. Hold the cable by its insulation in such a position that the metal terminal is about 3/16-inch from some grounded part of the engine. While holding the wire in this position, spin the engine over at normal cranking speed. If the magneto sparks this gap the trouble is not in the magneto. Now inspect the contact breakers. If the contact points are dirty they can be cleaned with a little clear gasoline. Make sure no particles of lint are left between the point surfaces if a brush or cloth is used. If the points are severely burned install a complete new contact breaker assembly. See that the contacts are properly adjusted. When fully open, there should be eighteen thousandths of an inch (.018") between the point surfaces. If there still is no spark the coil or condenser may be defective. Any service station with proper equipment can correct the situation.

# TILT PIN ADJUSTMENT FOR BEST PERFORMANCE

 Best performance will be realized by having the propeller shaft on a horizontal plane with regard to the bottom of the boat. Set tilt pin so that anti-cavitation plate (large plate immediately above propeller) is on a horizontal plane approximately one inch below the bottom of the boat or keel. To tilt motor too far under will tend to push the bow down. To tilt too far out will tend to push the stern down, consequently eliminating top performance.

#### SHIFT ROD ADJUSTMENTS

- 1. Move Gear Shift Lever to neutral position.
- If propeller turns clockwise and counter-clockwise freely, no adjustment is required.
- If propeller is engaged, loosen Control Rod Lock Nuts and set screw on Control Rod Adjustment Guide Nut. Turn Guide Nut clockwise or counter-clockwise until propeller is free.
- Tighten Control Rod Lock Nuts and set screw to complete the adjustment. Maintain a minimum of 1/64 of an inch clearance.

Favor forward adjustment. Unit should shift into forward with minimum movement from neutral position.

#### CO-SKIPPER ADJUSTMENT

Co-skipper adjustment is regulated by 3LGS58, Co-skipper Tension Adjustment Nut. Remove cotter pin 6LL1198, tighten nut to proper tension—replace cotter pin.

#### SYNCHRONOUS CONTROL

#### Magneto Control Adjustment

Turn twist grip control handle counter - clockwise to full throttle position. Stator plate should now be in full advance position. (The Stator Plate Control Pitman (56Q500) at bottom of Stator Plate Control Arm (3M511) groove). If not, loosen Control Shaft Arm Pivot Screw (6LL2213) and make proper adjustment. A small allowance should be made for slack in linkage.

## MAINTENANCE

#### COOLING SYSTEM

- Water for Cooling is provided by a "Positive Rotary Impeller" pump.
- Always be sure engine is cooling properly by watching for the tell-tale stream of water from outlet on bottom of Cylinder Head.
- 3. Should water fail to discharge:
  - a. Stop engine immediately.
  - b. Check intake holes on front of Lower Unit Body (6MM990-1) and outlet on Cylinder Head for obstructions.

 Use care if running motor in small test tank, re-using water continuously may cause overheating. Be sure water level is above intake openings.

#### SALT WATER INSTRUCTIONS

You will extend the life and performance of your motor, if using in salt water, by flushing fresh water through the motor after use. This may be done by running the motor in a barrel of fresh water.

# INSTRUCTIONS FOR COLD WEATHER USE

- Cold weather will not affect the running of your motor. However, to prevent freezing, when idle even for a few hours, drain water from motor by placing it in an upright position and pulling Starter Rope a few times.
- For long period storage see section "Instructions for Storing Motor."

# INSTRUCTIONS FOR STORING MOTOR

- Drain fuel system by running motor with Fuel Line Coupler disconnected from motor.
- Drain water from motor by placing it in an upright position and pulling Starter Rope a few times.
- Drain and refill Lower Unit (See section on "Lubrication.")
- Remove Spark Plugs and pour about two ounces of oil in each cylinder.
- 5. Squirt similar amount into Carburetor Intake.
- Turn motor over slowly several times. This will spread oil over all parts in the power head.
- 7. Important. With shift lever in forward position, turn motor over by turning the propeller in a clockwise direction. This will reverse the position of the water pump impeller blades so that they won't acquire a permanent set in one position.
- 8. Replace spark plugs.
- Store upright in clean dry place. We suggest that the specially designed shipping carton be used.

#### SPRING CHECK-UP SUGGESTIONS

- Remove plugs and clean or replace.
- Pull motor over several times with Starter Rope.
  - Wipe excess oil from around Spark Plug holes and replace Spark Plugs.
- Wipe entire motor clean and inspect for parts broken or out of adjustment.
- Put drop of light motor oil on all working parts and friction points.

#### LUBRICATION

The most important factor in the operation of any internal combustion engine is proper lubrication. Properly lubricate your motor and you will enjoy many years of highly satisfactory service. Improper lubrication will cause unnecessary wear and expense.

When draining the lower unit, the Filler Plug and Vent Screw should be removed and the motor placed in a vertical position to allow the oil to drain out.

When filling the unit with new oil, the motor should be placed in a horizontal position and the unit filled with Champion lower unit oil to the level of the Filler Plug. An oil can, preferably the pump type, should be used for filling the unit. For extreme cold weather operation only GX-80 oil may be used.

#### **FUEL SYSTEM**

- 1. This system includes gas lines, fuel pump, primer and coupling, and gas tank.
- 2. For better operating results:
  - Thoroughly mix and strain fuel.
  - Keep tank, lines and coupling clean.
  - Watch for and correct leaks in fuel system.
     Excessive air bubbles in 6MM421 Gas Line (other than during priming) indicate a leak in fuel system.
- To drain pump and carburetor, remove Coupler (6MM480) and run engine until dry.


#### WARNING!

Never raise lower unit above level of power head without first allowing water to drain from underwater exhaust housing. Always store motor in an upright position. Do not use so-called outboard motor gasoline or stove gas. Best results are obtained with regular gasoline.

#### WARRANTY REPAIR


You have received with this motor a warranty covering workmanship and materials. We will not be responsible for work performed and labor time spent by other than the manufacturer, unless such repairs are first authorized by us in writing.

## CARTER CARBURE TOR MODEL N 2440S




Part No.	Part Name	Part No.	Description
1A-102	Flange gasket	23A-19	Bowl ring gasket
2-173	Throttle valve	24-30	Float lever pin
3-1062S	Throttle shaft and lever assembly	25-33S	Needle and seat assembly
7-193	Choke valve	30A-68	Idle adjustment screw
12-471	Nozzle	37-73	High speed adjusting needle
14-506S	Choke lever and shaft assembly	39-10	Choke and throttle valve attaching screw (4)
15-54S	Bowl nut assembly	47-11	Idle port welsh plug
15A-12	Packing nut	47-31	Idle passage welsh plug
20-22	Needle seat gasket	61-369	Choke shaft spring
20-34	Packing nut gasket	61-475	Idle adjustment screw spring
20-110	Bowl nut gasket	61-575	Throttle return spring
21-163S	Float and lever assembly	116-16	Choke spring ball
23-47	Bowl	163-53	Main metering screw packing


## PHELON MAGNETO SPECIFICATION NO. OF-514V




Ref No.	Part No.	Description	Ref No.	. Part No.	Part No.	Description
1	F-1835	Coil	13	F-1356	Condenser	Screw
2	F-2052	Core Screw	14	F-147-C	Condenser	Screw Lockwasher
3	F-422	Ground Terminal Screw	15	FG-1770	Condenser	Group
4	F-564	Lead Wire Marker	16	FG-1793-A	Stator &	Core Assembly
5	FG-2086	Stator Assembly Complete	17	FG-2087	Flywheel	NOS W NEEDS OF STREET
6	FG-2061-J	Lead Wire	18	F-132		e Tube Clamp Screw
7	FG-2061-P	Lead Wire	19	F-147-C	Lead Wire	Tube Clamp Screw Lock-
8	F-204	Fixed Contact Screw	20	F-1775	Lead Wire	e Tube Clamp
9	F-147-C	Fixed Contact Screw Lockwasher	21	F-603	Lead Wire	e Tube
10	F-247	Fixed Contact Screw Plain Washer	22	F-539-E	Breaker C	Cam
11	FG-626	Breaker Assembly	23	F-906	Cam Wipe	er Felt
12	F-601	Breaker Connection Screw	24	F-600	Core Scre	w Lockwasher


## STARTER HOUSING AND ENGINE COVER, GAS TANK ASSEMBLIES








#### LOWER UNIT ASSEMBLY



#### PIVOT BASE AND BOAT BRACKET ASSEMBLIES



#### PARTS LIST

	PARTS	LIS	T	
Part	No. Part Name Reg'd	Part No.	Part Name	No. Reg'd
No.	Part Name Req'd Lower Unit Filler & Drain Plug 2	3M94	Steering Handle Grip	
3LGS2	Drive Gear Bearing 1	6LL96	Steering Handle Pivot	î
6MM4 2LH5	Ball Bearing Lock Ring 1	3M98	Steering Handle Friction	
1J6	Propeller Nut 1	SINISO	Washer	2
6LL8	Propeller 1	3M99	Steering Handle Support Cap	
2LH9	Shear Pin 1	6LL100	Steering Handle Assembly	1
6MM12	Propeller Shaft 1	6M104	Exhaust Manifold	1
6MM14	Pinion Gear 1		Exhaust Manifold Plate	
3LGS15	Lower Unit Gasket 1	6M105 6M106	Exhaust Manifold Gasket	
1J16	Grease Plug Gasket 2	6M108		4
2LH16	Rocker Arm Hinge Pin Gasket 1	01/11/09	Water Passage Cover Plate	1
2LH17	Gasket (Lock Screw) 1	6M110	Gasket	
56B18	Thrust Washer, Lower 1	OMITIO	Water Passage Cover Plate Assembly	1
6MM20	Drive Gear Assembly 1	CORRESA		
56B21	Thrust Washer, Upper 1	6MM111	Reverse Gear	
6MM25	Drive Spring 1	3LGS118	Rocker Arm	
6MM27	Drive Spring Friction Pin 1	3LGS119	Rocker Arm Hinge Pin	
56B29	Driveshaft 1	56B120	Lower Unit Cap Assembly	
3LGS32	Water Pump Rotor 1	3LGS121	Upper Shift Rod	1
3LGS36	Water Pump Housing1	3LGS122	Lower Shift Rod	
3LGS37	Lower Unit Control Rod 1	3LGS123	Rocker Arm Guide	
3LGS39	Water Pump End Plate (Top) 1	6MGS125	Reverse Spring	1
3LGS40	Anti-Cavitation Plate Assembly 1	6MM127 3LGS134	Reverse Spring Friction Pin Lower Shift Rod Lock	1
3LGS42	Driveshaft Housing 1	6M200	Center Main Bearing Assembly	
3LGS43	Lower Unit and Driveshaft	W. 8553 (C) (S) (A) (C) (A) (A)		1
~~ ~	Housing Stud (Front) 1	56Q206	Carburetor Adaptor Plate Gas-	3
2LL44	Motor Tilting Bracket 1	1J208	ket Cylinder Block Stud	1
1J50	Boat Bracket Tilting Pin Ass'y 1	56Q208	Carburetor Stud	2
3LGS52	Reverse Lock Catch 1	6LL209	Crankcase	
3LGS53	Reverse Lock Catch Washer 1	6M212	Magneto Mounting	
3LGS55	Control Rod Adjustment Nut	6M214	Center Main Bearing Race	
OT CICEC	and Guide 1 Reverse Lock Catch Spring 1	3L216	Screw, Center Main Bearing	-
3LGS56 3LGS58	Co-Pilot Tension Adj. Nut 1	OLLZIO	Lock	1
	Boat Bracket, R.H.	6M216	Screw, Stator Shaft Arm	1
2LL61	Boat Bracket, L.H.	56Q218	Bottom Main Bearing Seal	1
2LL62 1J68	Boat Bracket Clamp Screw Pad 2	6MM220	Cylinder Block Assembly	
3M70	Boat Bracket Clamp Screw	6M223	Cylinder Base Gasket	
SIMITO	Assembly 2	6M224	Head Gasket	
1.771	Tilting Bracket Friction Washer 2	6MM225	Cylinder Head	
1J71	Pivot Bolt Friction Washer 1	6M227	Screw, Cylinder Head	
1J72	Pivot Bolt Friction Washer 1	1J228	Washer, Shoulder Screw	
1J73		10220	Washer, Cylinder Head	
1J74	Co-Pilot Cushion 1	6M230	Crankshaft	
1J75	1 IVOL Dase Washer	6MM240	Connecting Rod	2
2LL76	Boat Bracket Spacer Pin 1		Piston Ring	
3LGS81	Lower Unit and Driveshaft	6M247 6M248	Wrist Pin	2
	Housing Stud (Rear) 1	0W1Z40	W118C 1 III	. 4

6M250

56Q400

6MM401

56Q402 6MM404

Motor Pivot Base and Tube

Intake Water Line

Carrying Handle

Water Line Fitting 1 Motor Base Gasket 1

6LL83

1J84

1J86

3LGS89

6LL93

Piston 2 Carburetor Adaptor Plate Assy. 1 Carburetor Gasket 1

Carburetor Inlet Elbow.

Carburetor

Part No.	Part Name	No. Reg'd	Part No.	Part Name	No. Req'd
56D409	High Speed Adjustment Knob		2K626	Spring Washer	
56E410	Choke Slide Assembly	. 1	2K630	Ratchet Assembly	1
6MM411	Choke Knob	1	2L635	Spring Cover	
56Q412	Choke Rod	1	3M636	Starter Spool Shim	As Reg'd
6MM413	Shoulder Screw, Choke Slide	2	6LL640	Starter Housing	200
6MM421 6M422	Gas Line, Long Gas Tank Outlet and Screen	1	3LGS710 3LGS712	Shift Lever Assembly Shift Lever Handle	1 1
6LL423	Gas Line, Fuel Pump Inlet		6M713	Control Shaft Arm Pivot	1
6MM424	Fuel Pump Inlet and Screen		3LGS717	Shift Bracket	1
6LL440	Control Guide Assembly	. 1	3LGS727	Shift Lever Pin	1
3M450	Steering Handle Rack and Wire Assembly	1	3LGS734 3LGS751	Shift Lever Cam Washer Shift Lever Catch	
6MM455	Synchronous Control Arm Roller		3M850 6LL868	Gas Tank Fuel Outlet Shroud Bracket, Upper	1
56Q457	Synchronous Control Cam		56Q875	Lower Shroud	
56Q460	Synchronous Control Arm	_ 1			
3M470	Fuel Pump Outlet	1	6LL877 6LL880	Shroud Support - Lower	
3M474	Gas Line Nipple			Upper Engine Cover	
6MM480	Auxiliary Primer Assembly		3M887	Gas Tank Handle Gasket	
3M481	Auxiliary Gas Line		6M889	Gas Tank	1
3M483	Valve, Fuel Pump		3M891	Gas Tank Handle	
6LL485	Fuel Pump Lock Ring		3M892	Gas Tank Relief Spring	1
6MM486	Fuel Pump Mounting Plate	. 1	3M893	Washer, Gas Tank Handle	4

## BE SURE TO GIVE MODEL AND SERIAL NUMBER OF MOTOR WHEN ORDERING PARTS

3M487 3M488	Fuel Pump Body 1 Fuel Pump Diaphragm 1	4LH896	Grommet, Shroud Mounting Ring 2
6MM489	Diaphragm Actuating Spring 1	4LH898	Shoulder Screw, Shroud
6MM491	Fuel Pump Gasket 1		Mounting Ring 2
6LL492 6LL493	Fuel Pump Spring Guide 1 Fuel Pump Spring 1	6LL898	Shoulder Screw, Shroud Mounting Ring 1
56Q500	Control Pitman Assembly 1	3M933	Steering Handle Spring Washer 1
6LL501	Magneto 1	3LGS941	Anti-Cavitation Plate Nut 1
6MGS503 3L505	Magneto Clamp Screw 2	3LGS942	Water Pump End Plate (Bottom) 1
6MM507	Flywheel Key 1 Magneto Clamp, Right Side 1	6M972	Spacer, Top Main Bearing 1
6LL509	Stator Shaft Arm 1	1J1001	Grommet, Choke Rod1
6MM510	Magneto Clamp Assembly 1		Grommet, Shroud Mounting1
3M511	Stator Plate Control Arm 1		Grommet, Water Line 1
6LL511	Stator Plate Indicator 1	3L1003	Spark Plug Connector 2
3M515	Control Shaft Collar 1	6M1006	Top Main Bearing Seal 1
3M517	Stator Plate Control Shaft Spring 1	6M1007 3LGS1011	Water Passage Tube "O" Ring 1 Anti-Cavitation Plate "O" Ring 1
56Q518	Control Shalt Bracket	V-96-30-3-3-3-3-3-3-3-3-3-3-3-3-3-3-3-3-3-3	Rocker Arm Guide "O" Ring 1
6LL520	Flywheel Assembly 1	2LH1013	Water Line "O" Ring 1
6MM551 1J574	Starter Plate1 Washer, Gas Cap Vent Screw_ 1	2LH1015 2LH1016	Propeller Shaft Seal 1 Lower Unit Cap Seal 1
1J579	Gasket, Gas Cap Vent Serew 1	2LH1017	Ball Bearing Lock Ring Seal 1
1K580	Gas Tank Cap Assembly 1	6M1018	Bearing Adaptor "O" Ring 1
3M605	Ready Pull Handle 1	3LGS1019	Driveshaft Seal 1
3M606	Handle Cable Lock 1	6LL1021	"O" Ring Steering Handle 1
6MM610	Starter Cable Assembly 1	6LL1031	Bumper, Shroud 6
2K611	Starter Spring Anchor Screw 1	3L1100-1	Center Main Needle Bearing 36
6M613	Starter Recoil Spring 1	6M1102	Wrist Pin Bearing 4
2L620	Starter Spool Assembly 1	4LS1103	Connecting Rod Needle
6LL622	Starter Ratchet Spring 2		Bearing 128

Part		No.	Part		No.
No.	Part Name	Req'd	No.		Req'd
6M1104	Main Bearing	3	2K2406	Screw, Lower Shroud	. 8
56B1108	Pinion Gear Thrust Bearing			Screw, Starter Housing Screw, Cavitation Plate	. 3
6MM1109 2LH1110	Driveshaft Bearing Propeller Shaft Ball Bearing		3L2408	Magneto Mounting Screw	
6LL1198	Co-Pilot Nut, Cotter Pin		2LH2414	Magneto Clamp Screw	
1J1200	Propeller Nut Cotter Pin		6MM2418	Starter Cable Anchor Screw	
1J1203	Synchronous Control Arm		6LL2419	Screw, Steering Handle	
	Spring Cotter		1J2502	Flywheel Nut	
2K1212 3M1223	Starter Spool Lock Ring Clamp, Gas Line	4	1J2601	Pivot Base and Carrying Handle Nut	
6MM1224 3LGS1227 2LH1230	Clamp, Gas Line Shift Lever Cam Snap Ring Lower Unit Ball Bearing Snap	1	1J2602	Crankcase and Cylinder Block Nut	
2LH1230	Ring Ring		3LGS2603	Lower Unit and Driveshaft	
2LH1231	Propeller Shaft Snap Ring	1	a a seculos en estados	Housing Nut	. 2
2LL1242	Shroud Clip, Rear	2		Lower Shift Rod Adjustment	
1J1602	Stator Plate Control Screw		01.50000	Nut	
1J1701	Pivot Base Screw, Rear		6M2607	Carburetor Nut	
1J1702	Pivot Base Screw	2	2K2704	Tilting Bracket Bolt Nut	
	Cylinder Block and Crank-	2	1 <b>J</b> 2900	Lock Washer, Pivot Base Screw	7 3
1 11702	case Screw			Lock Washer, Cylinder Block and Crankcase	2
1J1703	Cylinder Block and Crankcase Screw - Long	2		Lock Washer, Lower Unit and	. 3
	Deter - Zong	× 5	1	Book Washer, Bower oline and	
BE SURE	TO GIVE MODEL AND SER	IAL NU	MBER OF M	OTOR WHEN ORDERING PA	RTS
6LL1705	Screw, Control Shaft Bracket	2	I	Driveshaft Housing Stud	. 1
1J1708	Screw, Shift Bracket			Lock Washer, Pivot Base and	
FOR CHARGE IN CHARGE WATER AND	Screw, Control Shaft Collar	1		Carrying Handle Bolt	. 3
	Screw, Control Guide	2		Lock Washer, Motor Base Screw	9
	Screw, Water Passage Cover Plate	4	1J2906	Lock Washer, Control Guide	
4171713	Exhaust Manifold Screw		120200	Lock Washer, Control Shaft	
4K1713				Bracket	2
3M1714 2LL1731	Screw, Steering Handle Cap Lock Screw, Driveshaft Housin		VIII-Condition to A	Shift Bracket Screw Lock Washer	
6LL2002	Screw, Carrying Handle (Short)	1	1J2907	Carburetor Nut Lock Washer	. 2
1J2001 1J2005	Motor Base Screw Screw, Gas Tank Handle	2	1J2909	Driveshaft Housing Clamp Screw Lock Washer	
3LGS2006	Screw, Lower Shift Rod Lock	1	4K2910	Lock Washer, Fuel Pump Screw	4
4K2007	Carrying Handle Bolt			Lock Washer, Steering Handle	
3M2008	Screw, Fuel Pump	_ 4		Cap	
1J2200	Driveshaft Housing Clamp	-	1K2911	Flywheel Nut Lock Washer	. 1
1J2201	Screw, Center Main Bearing	2	3LGS2912	Lower Unit Body Stud Lock Washer	
6MM2203	Screw, Connecting Rod	. 2	2LL2915	Washer, Tilting Bracket Bolt	. 1
3LGS2207	Control Rod Adjustment Nut	2	1J3000	Starter Spring Dowel Pin	. 1
CT T 0010	Screw	1	6M3010	Center Main Bearing Dowel	. 1
6LL2213	Screw, Control Shaft Arm Pivo		4LH3118	Starter Plate Rivet	3
3M2215	Set Screw, High Speed Adjust- ment Knob		6M3300	Spark Plug	. 2
	ment Knob Set Screw, Steering Handle		3M3404	Connector, Gas Tank	
	Screw Screw	1	3LGS3501	Water Pump Rotor Pin	. 1
2LL2399	Tilting Bracket Friction Bolt	1	3LGS3502	Reverse Lock Pin	
56P2403	Synchronous Control Arm	HH 200	3LGS3503	Rocker Arm Guide Pin	
	Screw	2	3LGS3601	Crankcase Plug	. 2

	DECALS	223	"Majestic" Cruising Tank Decal	2
210	"Majestic" Side Decal 2	225	Forward - Neutral - Reverse Decal	L
211	"Majestic" Side Decal 2	227	Choke Decal (Pull)	L
215	"Majestic" Front Emblem 15	230	Tilting Decal	L
	· H.P. Decal1	231	Manufacturer's Decal	L
222	Instruction Decal - Tank 1	250	Shift Range Decal	L

#### ASSEMBLIES

### BE SURE TO GIVE MODEL AND SERIAL NUMBER OF MOTOR WHEN ORDERING PARTS

Part No.	State - 1 (1907)	fo. Part eq'd No.	Part Name No. Req'd
6MM890	Complete Gas Tank Assembly (Includes 6M422, 6MM480, 3M481, 3M483, 1K580, 3M850, 3MM887 (2), 6M889, 3M891, 3M892, 3M893 (4), 3M1223,	6ММ990-18	Connecting Rod and Piston Assembly (Includes 6MM240, 6M247 (2), 6M248, 6M250, 6M1102 (2), 4LS1103 (64)) 2
	1J2005 (4), 3M3205, 3M3404)	56Q990-28	Complete Set of Gaskets
6MM990-1	Lower Unit Body Sub-Assembly (Includes 6MM1, 6MM4, 3LGS36, 3LGS942, 3LGS1019, 6MM1109 (3)	L	(Includes 3LGS15, 1J16 (2), 2LH16, 2LH17, 3LGS89, 6M106 (2), 6M108, 56Q206, 6M223, 6M224, 6MM401, 6MM491,
56B990-6	Lower Unit Assembly (Includes 3LGS2 (2), 2LH5, 6MM12, 6MM14, 3LGS15, 1J16 (2), 2LH16, 56B18, 6MM20, 56B21, 6MM25, 6MM27, 56B29,		1J574, 1J579, 3M887 (2), 3LGS1011 (2), 2LH1015, 2LH1016, 2LH1017, 6M1018, 3LGS1019
*	3LGS32, 3LGS37, 3LGS40, 3LGS43, 6MM111, 3LGS118, 3LGS119, 56B120, 3LGS122, 3LGS123, 6MGS125, 6MM127, 3LGS134, 3LGS941, 3LGS1011 2LH1015, 2LH1016, 2LH1017, 56B1108, 2LH1110, 2LH1230, 2LH1231, 3LGS2006, 3LGS350 3LGS3503, 6MM990-1)	1,	Starter Housing Assembly (Includes 3M605, 3M606, 6MM610, 2K611, 6M613, 2L620, 6LL622 (2), 2K626, 2K630, 2L635, 3M636 (as req'd), 6LL640, 2K1212 (2), 6MM2418, 1J3000)

Your Majestic dealer is always ready and anxious to be of service. See him should

there be some questions about your motor

which you do not understand.

# Ten Golden Rules of Outboard Boating

- Respect the rules and regulations of waterway travel. Accidents can be eliminated if everyone possesses a thorough knowledge of outboard boating rules and ethics and then lives up to them.
- 2 Never cause undue disturbance by running your motor with open exhaust. Be considerate of those who may be seeking the peace and quietness they had hoped their lake place would give them.
- 3 Assist your fellow outboard enthusiasts should they be in trouble and need help. Perhaps your knowledge of boat and motor operation will help him to solve his problem and likewise add to his hours of pleasure.
- Avoid running too close to boats containing fishermen so as not to spoil their favorite phase of outdoor recreation. This is one of the many rules of good sportsmanship.
- Never overload your boat. Make sure that it is of proper size, construction and in good condition then carry only the number of passengers it can transport safely. When renting a boat, inspect it carefully and follow the above suggestions.

- Avoid stormy weather. If you are caught out in a heavy storm, proceed at moderate speed, seat all passengers on the floor, head into the wind at a slight angle and remain calm.
- **7** Give the right-of-way to larger craft. Your small outboard is more easily maneuvered than larger boats. Practice good seamanship; give all boats a wide berth when passing.
- 8 It is good sportsmanship to give the swimmer a fair break. Never run your boat near a swimming beach. Should it be necessary to do so, slow down and observe the rules of good seamanship.
- **9** Don't stand up. Standing up in any small boat can be dangerous. Sit down! It's safer.
- 10 Always wipe surplus gasoline and oil that may accumulate on the stern seat of your boat. While the fire hazard is very remote, it is well to practice precaution at all times.

Practice good sportsmanship and regard for others when traveling the waterways. Outboard boating is a pleasant, healthful form of recreation. Help others enjoy it!

Outboard Boating Club of America

# Outboard Motor Brands, Inc.

1325 N. E. Quincy

Minneapolis 13, Minnesota